

DRM-Rackmount Frame



Mini-Converter related details for use in the DRM and DRM2

| Mini-Converter | Max Power Consumption | Dimensions (W x D x H) | How Many Fit per DRM* | How Many Fit per DRM2 |
|---------------------|-----------------------|--|-----------------------|-----------------------|
| 3G-AM | 5 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 10 | 12 |
| 3G-AMA | 5 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 10 | 12 |
| 3GDA | 3 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 12 | 12 |
| 12G-AM | 10 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 5 | 12 |
| 12G-AM-R | 10 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 5 | 12 |
| 12G-AM-R-ST | 10 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 5 | 12 |
| 12G-AM-T | 10 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 5 | 12 |
| 12G-AM-T-ST | 10 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 5 | 12 |
| 12G-AM-TR | 10 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 5 | 12 |
| 12G-AMA | 10 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 5 | 12 |
| 12G-AMA-R | 10 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 5 | 12 |
| 12G-AMA-R-ST | 10 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 5 | 12 |
| 12G-AMA-T | 10 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 5 | 12 |
| 12G-AMA-T-ST | 10 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 5 | 12 |
| 12G-AMA-TR | 10 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 5 | 12 |
| 12GDA | 3 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 12 | 12 |
| 12GM | 12 watts | 5.76" x 4.02" x 0.90" (146.31 x 102.11 x 22.86 mm) | 4 | 12 |
| ADA4 | 3 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 12 | 12 |
| C10DA | 2 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 12 | 12 |
| FiDO-2R | 3 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-2R-12G | 2 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-2R-MM | 3 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-2T | 3 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-2T-12G | 3.5 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-2T-MM | 3 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-4R | 5 watts | 4.60" x 4.02" x 0.85" (117.00 x 102.11 x 21.60 mm) | 10 | 12 |
| FiDO-4R-MM | 5 watts | 4.60" x 4.02" x 0.85" (117.00 x 102.11 x 21.60 mm) | 10 | 12 |
| FiDO-4R-ST | 4 watts | 5.80" x 3.90" x 0.80" (147.00 x 99.00 x 20.00 mm) | 12 | 12 |
| FiDO-4T | 5 watts | 4.60" x 4.02" x 0.85" (117.00 x 102.11 x 21.60 mm) | 10 | 12 |
| FiDO-4T-MM | 5 watts | 4.60" x 4.02" x 0.85" (117.00 x 102.11 x 21.60 mm) | 10 | 12 |
| FiDO-4T-ST | 4 watts | 5.80" x 3.90" x 0.80" (147.00 x 99.00 x 20.00 mm) | 12 | 12 |

* Note: Maximum of this particular Mini-Converter, power consumption of all Mini-Converters can not exceed 50 watts in the DRM.

** Note: 24 Mini-Converters will fit if combined with the additional purchase of DRM2 Y-Cable, (12pack bundle of Y-Cable)

DRM-Rackmount Frame



Mini-Converter related details for use in the DRM and DRM2

| Mini-Converter | Max Power Consumption | Dimensions (W x D x H) | How Many Fit per DRM* | How Many Fit per DRM2 |
|----------------------|-----------------------|--|-----------------------|-----------------------|
| FiDO-R | 2 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-R-12G | 2 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-R-12G-ST | 2 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-R-MM | 2 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-R-SC | 2 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-R-ST | 2 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-T | 2 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-T-12G | 2 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-T-12G-ST | 2 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-T-MM | 2 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-T-SC | 2 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-T-ST | 2 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-TR | 3 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-TR-12G | 4 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FiDO-TR-MM | 3 watts | 4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm) | 12 | 24** |
| FS-Mini | 7 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 7 | 12 |
| GEN10 | 2 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 12 | 12 |
| HA5-12G | 11 watts | 4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm) | 4 | 12 |
| HA5-12G-T | 11 watts | 4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm) | 4 | 12 |
| HA5-12G-T-ST | 11 watts | 4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm) | 4 | 12 |
| HA5-4K | 10 watts | 5.76" x 4.02" x 0.90" (146.31 x 102.11 x 22.86 mm) | 8 | 12 |
| HA5-Fiber | 4.5 watts | 4.40" x 2.40" x 1.00" (112.00 x 61.00 x 25.00 mm) | 10 | 12 |
| HA5-Plus | 7.5 watts | 4.60" x 2.40" x 1.00" (116.84 x 60.96 x 25.4 mm) | 6 | 12 |
| HD5DA | 2.5 watts | 5.80" x 2.40" x 1.00" (131.00 x 61.00 x 25.00 mm) | 12 | 12 |
| HDP3 | 6.5 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 7 | 12 |
| Hi5-12G | 11 watts | 4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm) | 4 | 12 |
| Hi5-12G-R | 11 watts | 4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm) | 4 | 12 |
| Hi5-12G-R-ST | 11 watts | 4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm) | 4 | 12 |
| Hi5-12G-TR | 11 watts | 4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm) | 4 | 12 |

* Note: Maximum of this particular Mini-Converter, power consumption of all Mini-Converters can not exceed 50 watts in the DRM.

** Note: 24 Mini-Converters will fit if combined with the additional purchase of DRM2 Y-Cable, (12pack bundle of Y-Cable)

DRM-Rackmount Frame



Mini-Converter related details for use in the DRM and DRM2

| Mini-Converter | Max Power Consumption | Dimensions (W x D x H) | How Many Fit per DRM* | How Many Fit per DRM2 |
|----------------|-----------------------|--|-----------------------|-----------------------|
| Hi5-4K-Plus | 12 watts | 5.76" x 4.02" x 0.90" (146.31 x 102.11 x 22.86 mm) | 4 | 12 |
| Hi5-Fiber | 3 watts | 4.60" x 2.40" x 1.00" (116.84 x 60.96 x 25.40 mm) | 12 | 12 |
| Hi5-Plus | 7.5 watts | 4.60" x 2.40" x 1.00" (117.00 x 61.00 x 25.00 mm) | 6 | 12 |
| IPR-10G2-HDMI | 13 watts | 5.07" x 0.94" x 5.06" (128.80 x 23.90 x 128.40 mm) | 3 | 12 |
| IPR-10G2-SDI | 13 watts | 5.07" x 0.94" x 5.06" (128.80 x 23.90 x 128.40 mm) | 3 | 12 |
| IPT-10G2-HDMI | 13 watts | 5.07" x 0.94" x 5.06" (128.80 x 23.90 x 128.40 mm) | 3 | 12 |
| IPT-10G2-SDI | 13 watts | 5.07" x 0.94" x 5.06" (128.80 x 23.90 x 128.40 mm) | 3 | 12 |
| ROI-DP | 7 watts | 5.77" x 4.02" x 0.90" (146.56 x 102.11 x 22.86 mm) | 7 | 12 |
| ROI-DVI | 8 watts | 5.77" x 4.02" x 0.90" (146.56 x 102.11 x 22.86 mm) | 6 | 12 |
| ROI-HDMI | 8 watts | 5.77" x 4.02" x 0.90" (146.56 x 102.11 x 22.86 mm) | 6 | 12 |
| ROI-SDI | 7 watts | 5.77" x 4.02" x 0.90" (146.56 x 102.11 x 22.86 mm) | 7 | 12 |
| UDC | 7 watts | 5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm) | 7 | 12 |
| V2Analog™ | 3 watts | 5.10" x 2.40" x 1.00" (129.54 x 60.96 x 25.40 mm) | 12 | 12 |
| V2Digital™ | 3 watts | 5.10" x 2.40" x 1.00" (129.54 x 60.96 x 25.40 mm) | 12 | 12 |

* Note: Maximum of this particular Mini-Converter, power consumption of all Mini-Converters can not exceed 50 watts in the DRM.

** Note: 24 Mini-Converters will fit if combined with the additional purchase of DRM2 Y-Cable, (12pack bundle of Y-Cable)